

Trunk Amplifier_Triple Band



900-2100 MHz

JTD-L37L-GDW-50-37 (37dBm)

JIETONG DIGITAL

GET CONNECTED

LTE900+LTE1800+LTE2100

The JTD-L37L-GDW-50-37 Triple Band Bi-Directional Amplifier (BDA) (Trunk Amplifier / Line Amplifier) is designed to provide a more cost-effective solution than adding a new Base Transceiver Station (BTS) or RF Repeater to extend signal coverage and to improve communication quality in DAS system. And its easy installation and maintenance can help carrier get fast return. The Trunk Amplifier is working as a relay between the BTS or RF Repeater and distributed antennas. It receives the low-power signal from Trunk line of indoor distribution system via the coupler, linearly amplifies the signal and then retransmits it via the cables to the antenna distribution system. And the mobile signal is also amplified and retransmitted to the BTS via the opposite direction.

Key features

- Two signal ports with full duplex design.
- Aluminum-alloy casing with IP65 protection has high resistance to dust, water and corrosion.
- Linear power amplification to effectively suppress inter-modulation and spurious emission.
- Adopting filter with highly selectivity and low insertion loss eliminates interference between uplink and downlink.
- Stable and improved signal transmission quality.
- Smart Automatic Level Control (ALC) ensures output level stable and adjustable continuously.
- Auto Isolation check between service and donor signal level.
- Smart mode to auto-adjust gain according to the isolation and signal level received by donor side.
- Auto shut off function available for both uplink and downlink.

Advantages

- ☑ **Multi_standards/Multi_operators**
- ☑ **LCD real-time display to show the instant power and gain for each link.**
- ☑ **Smart function to set the proper gain automatically**
- ☑ **Shown output signal strength with numerical number.**



Specifications

Technical characteristics

Item	Specifications
System	LTE900/LTE1800/UMTS&LTE2100
Working Frequency	Uplink 885~915/1710~1775MHz/1920~1980MHz
	Downlink 930~960/1805~1870MHz/2110~2170MHz
Working Bandwidth	30MHz/65MHz/60MHz
Maximum Output Power	Uplink 0dBm per Band
	Downlink 37dBm per Band
Maximum Gain	Uplink 45dB
	Downlink 50dB
AGC Range	≥ 25dB
MGC Range	0~31dB@Step of 1 dB
VSWR	≤ 1.5
System Delay	≤ 1.0μs
Noise Figure	≤6dB
Spurious Emission	9kHz~1GHz: ≤ -36dBm
	1GHz~12.75GHz: ≤ -30dBm
Monitoring System	LCD real-time display to show the instant power and gain for each link.
LED Alarm	GREEN @ Normal, Red @ ALC 10dB,
RF Connector Type	2xN-Female
I/O Impedance	50Ω
Ingress Protection	Outdoor (IP65)
Operating Temperature	-25°C~55°C
Relative Humidity	≤95%
Dimensions	447x357x203mm
Weight	≤28Kg
Power Supply	AC100V ~240V, 50/60Hz, ≤180W
Smart Mode	Smart function to set the proper gain automatically
ISO	When AGC control over 25dB range, the ISO will turn to RED, and repeater will shut off
Mounting Type	Wall Mounting

Applications

To expand signal coverage or fill signal blind area where signal is weak or unavailable.

Outdoor: Airports, tourism regions, golf courses, tunnels, factories, mining districts, villages, ...

Indoor: Hotels, exhibition centers, basements, shopping malls, offices, parking lots, ...

