

RF Repeater_Penta Band

800-2600 MHz

TS-RP-C20L-LEDWH (20dBm)



LTE800+LTE900+LTE1800+LTE/UMTS2100+LTE2600

The RF Repeater provides an affordable solution to solve the indoor signal coverage problems due to signal fading and attenuation caused by architecture obstacles. And its easy installation and maintenance can help carrier get fast return.

The repeater is working as a relay between the BTS and mobiles. It picks up the strongest signal from BTS via the Donor Antenna, linearly amplifies the signal and then retransmits it via the Indoor Signal Distribution System to the weak/blind coverage area. And the mobile signal is also amplified and retransmitted to the BTS via the opposite direction.

Key features

- Two signal ports with full duplex design.
- Linear power amplification to effectively suppress inter-modulation and spurious emission.
- Stable and improved signal transmission quality.
- Compact size with stable performance.
- Smart Automatic Level Control (ALC) ensures output level stable and adjustable continuously.
- Auto Isolation check between service and donor antennas.
- Smart mode to auto-adjust gain according to the isolation and signal level received by donor site.
- Auto shut off function available for both uplink and downlink.
- Simple installation with external AC/DC adapter.
- Cost-effective for practical solutions.

Advantages

- Multi_standards/Multi_operators**
- Support antenna isolation detection**
- Smart function to set the proper gain automatically**
- LCD real-time display**



Specifications

Parameters		Uplink	Downlink
Frequency Range	LTE800	832 ~ 862MHz	791 ~ 821MHz
	LTE900	880 ~ 915MHz	925 ~ 960MHz
	LTE1800	1710 ~ 1785MHz	1805 ~ 1880MHz
	LTE/WCDMA2100	1920 ~ 1980MHz	2110 ~ 2170MHz
	LTE2600	2500 ~ 2570MHz	2620 ~ 2690MHz
Operation Bandwidth (-3dB)		Wide Band	
Maximum Gain		≥65dB	≥70dB
Output Power		≥15dBm	≥20dBm
MGC (Manual Gain Control)		31dB range/1dB step	
AGC (Automatic Gain Control)		≥25dB	
Spurious Emission	9KHz-1GHz	≤ -36dBm	
	1GHz-12.75GHz	≤ -30dBm	
Noise Figure		≤ 6dB	
VSWR		≤2.0	
Group Delay		≤1μs	
LED Alarm	Power LED	DC ON/OFF	
	AGC LED	GREEN @ Normal, Red @ ALC 10dB,	
ISO		When AGC control over 25dB range, the ISO will turn to RED, and repeater will shut off	
Smart Mode		Automatically adjust the gain in both links according to the specific environment.	
Output signal strength		Shown output signal strength with numerical number.	
RF Connector		N-Female	
Impedance		50Ω	
Power Consumption		≤35W	
Power Supply		Input: AC 110~240V	
Operating Temperature		-10°C~50°C	
Environment Conditions		IP40	
Dimensions (D x W x H)		310*170*65mm	
Weight		≤5.5KG	

Applications

To expand signal coverage or fill signal blind area where signal is weak or unavailable.

Outdoor: Airports, tourism regions, golf courses, tunnels, factories, mining districts, villages, ...

Indoor: Hotels, exhibition centers, basements, shopping malls, offices, parking lots, ...

