

JTD-MCPE-N3860B-X-150



JTD-MCPE-N3860B-X-150



380-6000MHz Directional Coupler

??: ????
1-4 Weeks
★ ★ ★ ★

[????????](#)

??

Electrical Specification										
Model	JTD-MCPE-N3860B-5-155	JTD-MCPE-N3860B-6-155	JTD-MCPE-N3827B-7-155	JTD-MCPE-N3860B-8-155	JTD-MCPE-N3860B-10-155	JTD-MCPE-N3860B-13-155	JTD-MCPE-N3860B-15-155	JTD-MCPE-N3860B-20-155	JTD-MCPE-N3860B-25-155	JTD-MCPE-N3860B-30-155
Frequency Range(MHz)	380-6000									
Coupling(dB)	5	6	7	8	10	13	15	20	25	30
Insertion Loss(dB)	2.15	1.75	1.40	1.2	0.85	0.55	0.45	0.35	0.3	0.3
Isolation	≥ 23	≥ 24	≥ 25	≥ 25	≥ 27	≥ 30	≥ 30	≥ 35	≥ 40	≥ 45
Coupling Deviation	±2.3	±1.5	±1.5	±1.5	±2	±2	±2	±2	±2	±2
VSWR	≤ 1.35									
IMD (dBc)	3 rd ≤ -150(@2×43dBm)									
Average Power(W)	300									
Impedance(Ω)	50									
Connector Type	N-F									
Appearance										
Dimension(mm)	202×50×36(without Connector)									
Dimension(mm)	240×70×36(with Connector)									
Weight(g)	650									
Color	Black									