JTD- FM Fiber Link

JTD- FM Fiber Link

87~108MHz FM???????(FM tunnel broadcast repeater)

??: ????

On Order

?????????

??

JTD- FM Fiber Link

-16

??????(???)??

?????????????CortexA9

??

???3U

????????????????????????????7

??

Frequency Range	87- 108 MHz	
Antenna connection	75 Ohm x 2	
Number of re-broadcast module	2 independent modules	
Number of re-broadcast channel (each module)	16 channel selective	
RDS rebroadcast	Pass-through	
Frequency resolution	0.1 MHz	
Remote connection	TCP/IP	
Break in source and interface	Analog stereo	
	AES	
	TCP/IP	PCM
RF Output Connector	SMA-Female	
RF Optical Output	0dBm, FC/APC	
Working Temperature	-25℃ to +55℃	
Relative Humidity	5- 95% RH	
Power Supply	90-246 VAC (Dual power modules)	
Power Consumption	= 100 Watt	
Dimensions	485mm X 360mm X 150mm	
Weight	= 6kg	

JTD- FM Fiber Link

-20??????(???)????20W

??

??

IP65???????????

Frequency Range	87- 108 MHz
RF Output Power	20 Watt
Optical input interface	FC/APC
Optical input range	-12 to 4 dBm
Gain control	0 to 30 dB
In band ripple	± 1dB
Remote connection	TCP/IP
Working Temperature	-40℃ to +60℃
Relative Humidity	5- 95% RH
Power Supply	90-246 VAC
Power Consumption	≤ 100 Watt
Dimensions	450mm X 315mm X 180mm
Weight	≤20kg