

## GT-LMR400



LMR-400



RF COAXIAL CABLE (30-6000MHz)

?: ????  
1-4 Weeks

[????????](#)

??

| Frequency(MHz) | Attenuation(dB/100m) | Avg. Power(KW) | Product Picture (GT-LMR400,GT-LMR400FR) |
|----------------|----------------------|----------------|---|
| 30 MHz         | 2.49                 | 3.33           |   |
| 50 MHz         | 3.18                 | 2.57           |   |
| 150 MHz        | 4.92                 | 1.47           |   |
| 220 MHz        | 6.23                 | 1.20           |   |
| 450 MHz        | 8.86                 | 0.83           |   |
| 900 MHz        | 12.81                | 0.58           |   |
| 1500 MHz       | 16.71                | 0.44           |   |
| 1800 MHz       | 18.40                | 0.40           |   |
| 2000 MHz       | 19.40                | 0.37           |   |
| 2500 MHz       | 22.00                | 0.33           |   |
| 3000 MHz       | 24.60                | 0.30           |   |
| 4000 MHz       | 28.87                | 0.28           |   |
| 6000 MHz       | 36.42                | 0.21           |   |