

JTD-MHSE-N3860B-150



JTD-MHSE-N3860B-15



380-6000MHz 3dB Hybrid Coupler

??: ????
1-4 Weeks
★ ★ ★ ★ ★

[????????](#)

??

Electrical Specifications	
Frequency Range (MHz)	380-6000
Insertion Loss (dB)	≤ 3.8
VSWR	≤ 1.3
Isolation(dB)	≥ 20
In-band Ripple (dB)	≤ ±0.8
PIM3 (dBc)	≤ -150 (2×43dBm)
Power Rating[W]	Average Power : ≤ 300 Peak Power : ≤ 1000
Impedance (Ω)	50
Connector	N - F
Appearance	
Dimension(without Connector)(mm)	216.7×43×42
Dimension(with Connector)(mm)	216.7×78.8×42
Color	Black