

JTDW-xWPS-xHF-N



136-174 & 350-520MHz VHF & UHF WILKINSON POWER SPLITTER

??: ????
1-4 Weeks
★ ★ ★ ★ ★

[????????](#)

??

| Model Number | JTDW-2WPS-VHF-NF JTDW-2WPS-UHF-NF | JTDW-3WPS-VHF-NF JTDW-3WPS-UHF-NF | JTDW-4WPS-VHF-NF JTDW-4WPS-UHF-NF |
|-------------------------|--------------------------------------|--------------------------------------|--------------------------------------|
| Frequency Band(MHz) | 136-174 & 350-520 | | |
| Split Loss(dB) | 3.0 | 4.8 | 6.0 |
| Insertion Loss(dB) | ≅ 0.4 | ≅ 0.5 | ≅ 0.6 |
| Isolation(dB) | ≅ 20 | ≅ 19 | ≅ 18 |
| VSWR | ≅ 1.3 | | |
| Power Rating(W) | 50(average per port) | | |
| RF Connector | N-female & SMA-female | | |
| Working Temperature(°C) | -35~+65 | | |
| Application | Indoor IP60 | | |
| Color | Black | | |