JTD36

IBMS AM Monitor

IBMS ????(IBMS AM Monitor)

??: ????
On Order

?????????

??

IBMS AM ?????? DSP ????????????? AM??????RF???SDR AM??????????????????????????????????????? AM ??? AM ??????????

Tuning Range	520-1710kHz
Tuning Step	1kHz
Antenna Port	BNC
Metering	
RF level	0 to 100dB μ V, ±1dB
Multipath	0 to 100%, ±1%
Signal to Noise Ratio	0 to 100dB, ±1dB
Audio level	+10 to-55dB, ±1dB
Audio Stream	Compatible audio steam
User interface	Web GUI interface
Ethernet	RJ45, 10/100M
Dimension	151*44*155 mm
Power	12V /1A ; < 12 Watt
Weight	< 2kg